

POWER TRANSFORMER PC MOUNT: WORLD SERIES

VPP10-5600

Electrical Specifications (@25C)

1. Maximum Power: 56.0VA

2. Input: **Series:** 230VAC, 50/60Hz; **Parallel:** 115VAC, 50/60Hz 3. Output: **Series:** 10.0V CT@ 5.60A; **Parallel:** 5.0V @ 11.2A

4. Voltage Regulation: 25% TYP @ full load to no load 5. Temperature Rise: 30C TYP (45C MAX allowed)

6. Insulation Resistance: 100MΩ

7. Hipot: 4000VAC between primary to secondary and windings to core.

Construction:

Dual bobbin construction with an insulated shroud, both made of a high temperature material that exceeds UL flammability requirements.

Safety:

Since the dual bobbin construction effectively reduces capacitance, electrostatic shielding is not required. World Series Transformers are designed and manufactured to meet the following agency approvals:











Agency File:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.

CSA: File LR 221330. C22.2 NO. 66, General Purpose.

TUV: File R72182067, EN 61558-1:2005+A1, EN61558-2-6:2009. Double Insulated. Non-inherently Short-Circuit-Proof.

A. Dimensions:

Units: In inches

Н	W	D	А	В	O	ML	MD	MW
1.812	3.0	2.50	0.600	0.300	1.900	ı	2.0	2.5

B. PIN DIM. : 0.045 SQ C. WT Lbs. : 1.70

D. Mounting Holes: 0.180 dia. x 4

Connections¹:

Input: Series – Pin 1 to Pin 6, Jumper Pin 4 to Pin 3

Parallel – Pin 1 to Pin 6, Jumper Pin 1 to Pin 4 and Pin 3 to Pin 6

Output: Series - Pin 7 to Pin 12, Jumper Pin 9 to Pin 10

Parallel - Pin 7 to Pin 12, Jumper Pin 7 to Pin 10 and Pin 9 to Pin 12


RoHS Compliance: As of manufacturing date February 2016, all standard products meet the requirements of 2015/863/EU, known as the RoHS 3 initiative.

* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.


Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571






SIDE VIEW



BOTTOM VIEW



Publish Date: August 25, 2021

¹ Primary and secondary windings are designed to be connected in series or parallel. Windings are not intended to be used independently.