

# Time is of the Essence!

Get to work faster with our rapid transit system:

## *TURBO EXPRESS*

The faster you get the products you need the faster you can get to work on building or testing the products and systems you sell. That's why we originated **EXPRESS** service—an innovative vehicle that guarantees overnight delivery of over 100 types of Weinschel microwave and RF components including:

- Fixed Attenuators
- High Power Fixed Attenuators
- Terminations and Loads
- Power Splitters and Dividers
- Adapters and Directional Couplers

**TURBO EXPRESS** is a joint effort with New England's noted distributor Sickles Distribution Sales. They maintain a large inventory of standard Weinschel products and ship your order overnight to any destination in the United States and Canada. They accept VISA or MASTERCARD or your purchase order. Just dial the **EXPRESS** number, **1-800-542-4457**.

Sickles Distribution is increasing the efficiency with which we respond to your expedited needs. Applications and engineering questions should still be directed to our headquarters in Maryland.

**EXPRESS**  
800-542-4457

*Sickles Distribution Sales*

# Weinschel

CORPORATION

*An MCE Company*

5305 Spectrum Drive, Frederick, Maryland 21703-7362  
800-638-2048 • Tel: 301-831-4701 • Fax: 301-831-4570  
e-mail: sales@weinschel.com • Web: www.weinschel.com

**EXPRESS**  
1-800-542-4457

Fax Sickles at 781-863-0684  
e-mail Sickles at sickles@gis.net



Certificate No. 94-289C

WEINSCH00001 X

### Fixed Attenuators

Model Number	Connector Type	Frequency Range (GHz)	Average Power (Watts)	Peak Power (kW)	Nominal Attenuation Value (dB)	SWR <sup>1</sup>
1	N	dc-12.4	5	1	1 thru 10, 20, 30, 40, 50, 60	1.15-1.25
1W	N	dc-4.0	2	0.25	1 thru 10, 20, 30	1.15
2	N	dc-18.0	5	1	1 thru 10, 20, 30, 40, 50, 60	1.15-1.35
3M/3T	SMA	dc-12.4	2	0.5	1 thru 10, 20, 30, 40, 50, 60	1.15-1.25
4H	SMA	dc-18.6	2	0.25	1 thru 10, 20, 30	1.15-1.35
4M/4T	SMA	dc-18.0	2	0.5	1 thru 10, 20, 30, 40, 50, 60	1.15-1.35
4W	SMA	dc-3.0	2	0.25	1 thru 10, 20, 30, 40	1.20-1.30
18W	BNC	dc-12.4	5	1	1 thru 10, 20, 30	1.25-1.35
23	N	dc-18.0	10	1	1, 2, 3, 6, 10, 20, 30, 40, 50, 60	1.15-1.35
24	N	dc-8.0	50	5	3, 6, 10, 20, 30	1.20-1.30
33	N	dc-8.0	25	5	3, 6, 10, 20, 30	1.20-1.30
34	N	dc-4.0	25	5	3, 6, 10, 20, 30	1.10-1.20
37	N	dc-8.5	25	5	3, 6, 10, 20, 30	1.15-1.25
40	N	dc-1.5	150	10	3, 6, 10, 20, 30, 40	1.10
41	SMA	dc-18.0	10	1	1, 2, 3, 6, 10, 20, 30	1.20-1.35
44	N	dc-18.0	5	1	1 thru 10, 20, 30, 40, 50, 60	1.15-1.25
45	N	dc-1.5	250	10	3, 6, 10, 20, 30, 40	1.10
46	N	dc-18.0	25	1	3, 6, 10, 20, 30, 40	1.20-1.35
47	N	dc-18.0	50	1	10, 20, 30, 40	1.20-1.35
48	N	dc-18.0	100	1	20, 30, 40	1.25-1.45
49	N	dc-8.5	150	10	3, 6, 10, 20, 30, 40	1.25-1.35
54	SMA	dc-40.0	2	0.2	3, 6, 10, 20, 30	1.35-1.60
69	SMA	dc-18.0	5	0.5	1 thru 10, 20, 30	1.15-1.35
3330A 3331A	SMA	dc-18.0	2	0.25	1 thru 30	1.20-1.50

### Directional Couplers--Octave & Multi-Octave

Model Number	Frequency Range (GHz)	Coupling (dB)*	Frequency Flatness* (dB)	Minimum Directivity (dB)	Maximum SWR	Maximum Insertion Loss above Coupling Loss (dB)	Maximum Peak** Power (kW)	Maximum Average** Power (W)
1536RA-10	1.0-2.0	10±1.20	±0.75	20	1.20	0.2	3	50
1536RA-20	1.0-2.0	10±1.20	±0.75	20	1.20	0.2	3	50
1537RA-10	2.0-4.0	10±1.20	±0.75	20	1.25	0.2	3	40
1537RA-20	2.0-4.0	20±1.20	±0.75	20	1.25	0.2	3	40
1538RA-10	0.5-2.0	10±1.20	±0.75	20	1.20	0.2	3	50
1538RA-20	0.5-2.0	20±1.20	±0.75	20	1.20	0.2	3	50
1538RA-30	0.5-2.0	20±1.20	±0.75	20	1.20	0.2	3	50
1540RA-20	1.0-4.0	20±1.00	±0.30	20	1.25	0.25	3	50

\* Coupling includes frequency flatness. Coupling measurement is referenced to the Input Port.  
\*\* Peak and average power handling capability only apply if the main line is terminated in a 1.25 maximum SWR for 10 dB models and 1.75 for 20 and 30 dB models.

### Terminations

Model Number	Connector Type	Frequency Range (GHz)	Average Power (Watts)	Peak Power (kW)	SWR <sup>1</sup>
1404N	N	dc-18.0	1	1	1.02-1.08
1406A	SMA	dc-18.0	2	0.5	1.05-1.21
1408	SMA	dc-18.0	2	0.5	1.04-1.15
1419	SMA	dc-18.0	10	1	1.20-1.35
1424	N	dc-12.4	5	5	1.03-1.40
1427	N	dc-10.0	25	5	1.10-1.15
1426	N	dc-8.0	50	5	1.20-1.30
1436R 1437R	SMA	dc-3.0	1.5 2	0.5 0.75	1.08-1.15
1451	2.92mm	dc-40.0	1	0.5	1.15-1.25
1455	N	dc-18.0	2	1	1.10-1.20
RS3016	SMA	dc-18.0	1	0.25	1.05-1.21

### Inside dc Blocks

Model Number	Connector Type	Frequency Range (GHz)	Voltage Rating (max)	SWR <sup>1</sup>	Insertion Loss (dB)
7003	N	0.01-18.0	+50 V	1.35	0.8
7006	SMA	0.01-18.0	+50 V	1.35	0.8

### Resistive Power Splitters & Dividers

Model NO.	Type	Frequency Range (GHz)	MAX Input Power CW (W)	Insertion Loss (MAX dB)	SWR <sup>1</sup>	Connector TYPE
1506A	Divider	dc-18.0	1	7.5	1.25-1.35	Type N (M/F)
1507R	Splitter	dc-4.0	1	6.5	1.15-1.25	SMA (F)
1515	Divider	dc-18.0	1	7.5	1.25-1.35	SMA (M/F)
1579	Splitter	dc-26.5	0.5	8.5	1.25-1.35 <sup>2</sup>	3.5 mm (F)
1580	Divider	dc-26.5	1	8.5	1.25-1.7	3.5 mm (M/F)
1870	Splitter	dc-18.0	1	7.5	1.30	Type N (M/F)

### Precision Adapters

Model Number	Connector Type	Frequency Range (GHz)	SWR <sup>1</sup> (Maximum)	Insertion <sup>1</sup> Loss (dB)	Repeatability <sup>1</sup>
1568, -1	SMA Bulkhead (f-f)	dc-26.5	1.15-1.25	<0.20-0.35	0.010-0.020
1587	SMA (f-f)	dc-26.5	1.15-1.20	<0.20-0.35	0.010-0.020
1588	SMA (m-f)	dc-26.5	1.15-1.20	<0.20-0.35	0.010-0.020
1589	SMA (m-m)	dc-26.5	1.15-1.20	<0.20-0.35	0.010-0.020

1. Varies with frequency. 2. Equivalent Source SWR.