
## **Bussmann**®

## **Time-Delay Ceramic Fuses** For $\frac{1}{4}$ × 1 $\frac{1}{4}$ (6.3mm × 32mm)

# MDA **MDA-V**



#### **Time-Current Characteristics**

Rated	Percent of Rating						
Current	110%	135%	200%				
²∕ <sub>10</sub> -30	4 hrs. (min)	60 min. (max)	120 sec. (max)				

### CURRENT IN AMPERES

C€ CE logo denotes compliance with European Union Low Voltage Directive (50-1000 Vac, 75-1500 Vdc). Refer to BIF document #8002 or contact Bussmann Application Engineering at 636-527-1270 for more information.

#### **Electrical Characteristics**

	Rated ed Voltage <sup>6</sup>		Interrupting Rating <sup>1,4,7</sup>		Pre-arcing I²t (A²Sec)		Typical Total Clearing <sup>3</sup> I <sup>2</sup> t (A <sup>2</sup> Sec)		Typical Voltage Drop <sup>2</sup> Volts at	Agency* Approvals	
Rated									100% Rated	U.L UR CSA	
Current <sup>5</sup>	AC (Max.)	DC (Max.)	AC	DC	AC	DC	AC	DC	Current	L L	5 0
2/10	250V	250V	35A	35A	.44	.40	.28	2.57	1.78	•	•
1/4	250V	250V	35A	35A	.50	.56	.70	.57	3.41	•	•
1/2	250V	250V	35A	35A	1.67	4.34	2.25	4.64	1.51	•	•
3/4	250V	250V	35A	35A	5.21	6.55	6.80	6.83	1.02	•	•
1	250V	250V	35A	35A	10.08	8.71	12.53	10.28	.96	•	•
1½	250V		100A		24.50		30.00		.70	•	•
2	250V		100A	100A	36.53	24.95	73.43	73.55	.58	•	•
21/2	250V		100A		27.40		36.95		.23	•	•
3	250V	250V	100A		35.70		144.00		.22	•	•
4	250V		200A		141.50		165.90		.18	•	•
5	250V		200A		310.00		368.30		.17	•	•
6	250V		200A		534.30		567.20		.16	•	•
7	250V		200A		591.30		364.00		.15	•	•
8	250V		200A		898.20		906.10		.13	•	•
10	250V	250V	200A	200A	843.00	1515.00	924.50	1661.00	.12	•	•
15	250V	250V	750		238.10	216.90	359.70	299.90	.13	•	•
20	250V		1500		582.00		761.00		.13	•	
25	250V		1500		1097.00		1410.00		.13	.	•
30	250V		1500		1565.00		2064.00		.14		•

\*Approvals: U.L. Listed, Std. 248-14, Guide JDYX, File E19180; CSA Certification, Class 1422-01, File 53787.

Interrupting ratings for ½2-2VA were measured at 70% - 80% power factor on AC, and at a time constant described in U.L. 198L. Voltage drop was measured at 25°C±3°C ambient temperature at rated current. 1.

2.

I<sup>2</sup>t was measured at listed interrupting rating and rated voltage. З.

Interrupting rating for MDA 1/32-30A @ 125 Vac is 10,000A. Interrupting rating listed corresponds to maximum rated voltage. 4.

Other available sizes include 1/32, 1/16, 1/10, 1/8, 15/100, 3/10, 3/8, 4/10, 6/10, 1/4, 15/10, 28/10, 33/10, 4/2, 6/4, and 12. 5.

6. DC ratings are self certified.

7. Interrupting ratings for 25A, 30A were measured at 90%-100% power factor on AC.




Form No. MDA Page 1 of 2 BIF Doc #2002

## **Bussmann**®


# **Time-Delay Ceramic Fuses** For $\frac{1}{4}$ " × 1 $\frac{1}{4}$ " (6.3mm × 32mm)

MDA MDA-V

### 1.0 Typical Voltage Drop (At 25° C Ambient Temperature)



### 2.0 Ambient Temperature Effect Chart (Derating Curve)



The only controlled copy of this BIF document is the electronic read-only version located on the Bussmann Network Drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Bussmann reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Bussmann also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.



Form No. MDA Page 2 of 2 BIF Doc #2002